



Specifications Noxion LED Tube T8  
Avant (EM/Mains) Standard Output  
18W 1800lm - 865 Daylight | 120cm -  
Replaces 36W

[View Product](#)

General Information

|                             |                                                                                     |
|-----------------------------|-------------------------------------------------------------------------------------|
| SKU                         | 237753                                                                              |
| EAN                         | 8719157011143                                                                       |
| Brand                       | Noxion                                                                              |
| Manufacturer Name           | Noxion Avant LEDtube T8 Standard (EM/Direct) 1200mm 18W/865 (36W eqv.) with Starter |
| Full box quantity           | 25                                                                                  |
| Any Lamp all-in warranty    | 5 Years                                                                             |
| Energy efficiency class old | A+                                                                                  |
| Average Lifetime (h)        | 50000                                                                               |

Technical Information

|                             |               |
|-----------------------------|---------------|
| Technology                  | LED           |
| Dimmable                    | Not Dimmable  |
| Cap / Base                  | G13           |
| Rotatable                   | No            |
| Colour Code                 | 865 Daylight  |
| Colour temperature (Kelvin) | 6500 Daylight |
| Colour Rendering (Ra)       | 80-89         |
| Colour of Light             | White         |
| Light colour options        | Single Color  |
| Luminous Efficacy (lm/W)    | 100           |

|                       |             |
|-----------------------|-------------|
| Product Type Category | LED Tube T8 |
|-----------------------|-------------|

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Lamp Information

|                      |     |
|----------------------|-----|
| LED Starter included | Yes |
|----------------------|-----|

|                  |    |
|------------------|----|
| Requires Ballast | No |
|------------------|----|

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
|-----------------------|-----------------------------------------------------------------------|

|                 |                 |
|-----------------|-----------------|
| LED Tube Output | Standard Output |
|-----------------|-----------------|

|         |       |
|---------|-------|
| Housing | Glass |
|---------|-------|

|        |       |
|--------|-------|
| Series | Avant |
|--------|-------|

## Dimensions

|        |       |
|--------|-------|
| Length | 120cm |
|--------|-------|

|             |      |
|-------------|------|
| Length (mm) | 1200 |
|-------------|------|

|               |    |
|---------------|----|
| Diameter (mm) | 28 |
|---------------|----|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

